

Caja de Montaje Remoto / Semi-Empotrada / Puerta Vidrio Ahumado con Cerradura / Bus EIA-485 4 Hilos / 1,828.8 m (6,000 ft)

SKU: ABF-1DB Marca: NOTIFIER Categoría: NOTIFIER

Garantía: 3 años

$6,609.98

Precios con IVA incluido

DESCRIPCIÓN

La ABF1DB es una caja de montaje remoto semi-empotrada diseñada para alojar un módulo anunciador de la serie ACS (ACM/AEM-24AT o ACM/AEM-48A) dentro del sistema de detección de incendios ONYX. Permite ubicar la anunciación fuera del gabinete principal del panel, resultando ideal para instalaciones en entradas de cuartos de bombas, recepciones u otras zonas donde se requiere visibilidad y control local. El módulo alojado se comunica con el panel de detección mediante bus EIA-485 a 4 hilos, soportando distancias de hasta 1,828.8 m (6,000 ft). La caja incorpora puerta de vidrio ahumado con cerradura de llave para proteger los indicadores y controles contra manipulación no autorizada. Su construcción de metal pintado en negro asegura resistencia para uso prolongado en entornos profesionales.

Características Generales
Alojamiento remoto semi-empotrado para módulo anunciador ACM/AEM-24AT o ACM/AEM-48A
Puerta de vidrio ahumado con cerradura de llave para control de acceso
Orificios ciegos para conducto de 1/2 in (1.27 cm)
Compatible con paneles ONYX NFS2-3030, NFS2-640, NFS-320(C) y NFS-320SYS
Comunicación con panel vía bus EIA-485 a 4 hilos, hasta 1,828.8 m (6,000 ft)
Construcción de metal pintado en negro para uso prolongado

Desempeño y Comunicación
Bus EIA-485 a 4 hilos
Alcance máximo: 1,828.8 m (6,000 ft)
Compatible con módulos ACM/AEM-24AT y ACM/AEM-48A
Integración con paneles ONYX NFS2-3030, NFS2-640, NFS-320(C), NFS-320SYS

Físicas y Montaje
Tipo: Semi-empotrada en pared
Puerta de vidrio ahumado con cerradura de llave
Orificios ciegos para conducto de 1/2 in (1.27 cm)
Construcción de metal pintado en negro

Contenido del Paquete
Caja de montaje remoto ABF1DB
Puerta de vidrio ahumado con cerradura

ESPECIFICACIONES

Característica 1	**Protección física con cerradura de llave para control de acceso restringido**
Característica 2	**Comunicación EIA-485 a 4 hilos hasta 1,828.8 m (6,000 ft) del panel**
Característica 3	**Semi-empotrada en pared para ubicación flexible de anunciadores**
Característica 4	**Orificios ciegos para conducto de 1/2 in (1.27 cm) facilitando cableado**
Característica 5	**Construcción metálica pintada en negro para durabilidad en entornos exigentes**
Característica 6	**Compatible con módulos ACM/AEM-24AT y ACM/AEM-48A de serie ACS**

MEMORIA TÉCNICA · ABF-1DB

Número de parte de esta ficha: ABF-1DB. La información corresponde a esta variante.

DN-6862:D • 2/28/17 — Page 1 of 4
ACS Series Annunciators
ONYX
®
- Series
ACM/AEM-24AT, ACM/AEM-48A
DN-6862:D D-95
Annunciator Control Systems
General
The ONYX® Series ACS Annunciators provide a modular line of products for annunciation and control of the NOTIFIER ONYX® Series Intelligent Fire Alarm Control Panels, Network Control Annunciators, and NOTIFIER's legacy addressable panels. The ACS line provides arrays of LEDs to indicate point status and, in some versions, switches to control the state of output circuits. These ACS units use a serial interface and may be located at distances of up to 6,000 feet (1,828.8 meters) from the panel.
Features
- Speaker control mode for use with XPIQ and the following panels: NFS2-3030, NFS2-640, NFS-320(C) and NFS-320SYS. Enables the ACS to control operation of groups of multi-channels mapped to groups of multi-speakers.
- Compatible with existing annunciators.
- Color-programmable LEDs.
- On-board end-of-line resistors can be enabled/disabled by setting a switch.
- Alarm/Circuit On and Trouble LED per-point option or more dense Alarm-only option.
- Touch-pad control switch option for remote control of system relays; or silence, reset, and evacuate.
- LEDs may be programmed to display status of indicating circuits or control relays as well as system status conditions.
- System Trouble LED indicator.

- On-Line/Power LED indicator.
- Alarm and trouble resound with flash of new conditions.
- Local sounder for both alarm and trouble conditions with silence/acknowledge button (program options).
- May be powered by 24 VDC from the panel or by remote power supplies.
- Microprocessor-controlled electronics, fully supervised.
- Slip-in custom labels, lettered with standard typewriter or LabelEase program.
- Plug-in terminal blocks for ease of installation and service.

Construction

The ACS modules are provided in two basic controller modules, each with its expander module. The ACM-24AT provides 24 annunciation and control points per module, each with a red, green, or yellow Alarm/Circuit On LED, a yellow Trouble LED, and a touch-key switch. The ACM-48A provides 48 annunciation points per module, each with a red, green, or yellow Alarm/Circuit On LED (for annunciating control relays, the LED indicates ON/OFF).

On the ACM-24AT, each LED point is individually color-programmable. On ACM-48A, each column of 24 LED points can be color-configured using a DIP switch.

Temperature and humidity ranges: This system meets NFPA requirements for operation at 0°C to 49°C (32°F to 120°F); and at a relative humidity (noncondensing) of 85% at 30°C (86°F) per NFPA, and 93% ± 2% at 32°C ± 2°C (89.6°F ± 1.1°F) per ULC. However, the useful life of the system's standby batteries and the electronic components may be adversely affected by extreme temperature ranges and humidity. Therefore, it is recommended that this system and all peripherals be installed in an environment with a nominal room temperature of 15°C to 27°C (60°F to 80°F).

Installation

The ACS Series annunciator and control subsystems use modular hardware assemblies which allow the custom configuration of the annunciator panel to fit the individual job requirements.

Standard backboxes and mounting hardware schemes, including special remote cabinets, allow the annunciators to be constructed and configured with other system components.

When used with the NFS2-3030, NFS2-640, NFS-320 or legacy panels, the ACS modules can be used for manual selection of speaker and telephone circuits. In this application, they are typically mounted in the main control near the microphone and telephone handset.

For remote annunciation applications, the modules are typically mounted in special ABF or ABS boxes. Control switch key locks (AKS-1B) are available.

Communication between the ACS Series annunciators and the host Fire Alarm Control Panel is made through an EIA-485 multi-drop loop, eliminating the need for costly wiring schemes. Four wires are required, two for the EIA-485 communications (twisted pair), and two for 24 VDC regulated power.

Retrofit of ACS Series annunciators into existing systems is easily accomplished. Software may require upgrading, and some legacy panels may require an interface board.

All field-wiring terminations use removable, compression-type terminal blocks for ease of installation, wiring, and circuit testing.

ACM/AEM-24AT

ACM/AEM-48A

6862at24.wmf 6862a48.wmf

Operation

The ACS Series annunciator and control system provides the NOTIFIER system with up to 32 remote serially connected annunciators, each with a capacity of 96 points, for a total capacity of 3072 points (subject to the capability of the FACP). The NFS2-3030 and NCA-2 are capable of using the full 96 points.

Local or remote power supplies and serial communications allow the ACS to be located virtually anywhere in the protected premises.

On NFS-320, NFS2-640, NFS2-3030, NCA-2 and the legacy panels, system alarm and/or trouble conditions may be annunciated on a per-point basis, or in a grouped or zone configuration.

Control of system operational controls, such as Signal Silence, System Reset, and local annunciation controls (such as Local Acknowledge and Lamp Test) may be accomplished through the module's rubber keypad.

Product Line Information

"C" suffix indicates ULC-Listed model.

ACM-24AT: (see figure) The Annunciator Control Module-24AT contains 24 color-programmable (red/green/yellow) Active and 24 yellow Trouble LEDs, 24 momentary touch-pad switches, a System Trouble LED, an On-Line/Power LED, and a local piezo sounder with a silence/acknowledge switch for audible indication of alarm and trouble conditions. Includes instructions. 8.375" (21.27 cm) high; 4.375" (11.11 cm) wide.

AEM-24AT: The Annunciator Expander Module-24AT expands the ACM-24AT by 24 system points. The AEM-24AT is identical in size and in frontal appearance to the ACM-24AT. Up to three of these expander modules can be supported by an ACM-24AT, for a maximum of 96 system points. 8.375" (21.27 cm) high; 4.375" (11.11 cm) wide. NOTE: The AEM-24AT cannot be used to expand the ACM-48A.

ACM-48A: (see figure) The Annunciator Control Module-48A contains 48 color-programmable (red/green/yellow) Active LEDs, a System Trouble LED, an On-Line/Power LED, and a local piezo sounder with a Silence/Acknowledge switch for audible indication of alarm and trouble conditions. Includes instructions. 8.375" (21.27 cm) high; 4.375" (11.11 cm) wide.

AEM-48A: The Annunciator Expander Module-48A expands the ACM-48A by 48 system points. The AEM-48A is identical in frontal appearance to the ACM-48A. One expander module can be supported by an ACM-48A, providing a maximum of 96

points (subject to the capability of the FACP). 8.375" (21.27 cm) high; 4.375" (11.11 cm) wide. NOTE: The AEM-48A cannot be used to expand the ACM-24AT.

ABS-1B(C): (see figure) The Annunciator Surface Box-1B (black) provides for the remote mounting of one annunciator module in a surface-mount enclosure. Knockouts are provided for use with 1/2" (1.27 cm) conduit. The annunciator mounts directly to the ABS-1B(C) without a dress plate. 8.5" (21.59 cm) high x 4.5" (11.43 cm) wide x 2" (5.08 cm) deep. NOTE: The ABS-1B(C) will not support the installation of the AKS-1B Annunciator Key Switch.

ABS-1TB(C): The ABS-1TB(C) is an attractive surface-mount backbox for mounting one ACS Series Annunciator. Unlike the ABS-1B(C), the ABS-1TB(C) has an increased depth that allows mounting of the AKS-1B Annunciator Key Switch. Black, 9.938" (25.24 cm) high x 4.625" (11.75 cm) wide x 2.5" (6.35 cm) deep. NOTE: An earlier gray model, ABS-1TB, will not accommodate the ACM/AEM-24AT or ACM/AEM-48A. The slightly deeper ABS-1TB(C) will accommodate both the ACM/AEM-24AT or ACM/AEM-48A models and the ACM-16AT/ACM-32A Series (see DN-0524).

ABS-2B: The Annunciator Surface Box-2B (black) provides for the surface mounting of one ACM-24AT/AEM-24AT combination or one ACM-48A/AEM-48A combination. Knockouts are provided for use with 1/2" (1.27 cm) conduit. The annunciators mount directly to the ABS-2B without a dress plate. 8.5" (21.59 cm) high x 8.92" (22.66 cm) wide x 2" (5.08 cm) deep. NOTE: The ABS-2B will not support the installation of the AKS-1B Annunciator Key Switch.

ABF-1B(C): (see figure) The Annunciator Flush Box-1B (black) provides for the remote mounting of a single annunciator module in a flush-mount enclosure. Knockouts are provided for use with 1/2" (1.27 cm) conduit. The ABF-1B includes a painted black metal trim plate [11" (27.94 cm) high x 6.25" (15.875 cm) wide], mounting hardware, and an adhesive-backed annunciator label for the dress plate. 9.938" (25.24 cm) high x 4.625" (11.75 cm) wide x 2.5" (6.35 cm) deep.

ABF-2B: The Annunciator Flush Box-2B (black) provides for the flush mounting of two annunciator modules. Includes a painted black metal trim plate [11" (27.94 cm) high x 10.625" (26.99 cm) wide] and adhesive-backed annunciator label. 9.938" (25.24 cm) high x 9.188" (23.34 cm) wide x 3.75" (9.525 cm) deep.

ABF-4B: (see figure) The Annunciator Flush Box-4B (black) provides for the remote mounting of one to four annunciator modules. Knockouts are provided for use with 1/2" (1.27 cm)

ACM/AEM-24AT ACM/AEM-48A
6862at24.wmf 6862a48.wmf
ABS-1B(C)
ABF-1B(C)
50439d3.tif
50439d2.tif

conduit. The flush-mounted ABF-4B includes a painted black metal trim plate [11" (27.94 cm) high x 19.375" (49.21 cm) wide] and an annunciator label. 9.938" (25.24 cm) high x 17.75" (45.09 cm) wide x 2.5" (6.35 cm) deep.

ABF-1DB(C), ABF-2DB(C), ABS-4D(C): The ABF-1DB(C), ABF-2DB(C) and ABS-4D(C) are semi-flush-mount backboxes for ACS Series Annunciators. The ABF-1DB(C)mounts one annunciator module; the ABF-2DB mounts two modules; the ABS-4D(C) mounts up to four modules. The ABS-4D(C) Series can also accommodate the NCA-2 network annunciator, using the NCA-2 Retro Kit (NCA-2Retro); the NCA-2 is mounted in the center position with a blank plate (BMP-1) mounted on each side. Black with an attracted smoked glass door and keylock. The ABS-4D(C) is hinged on the bottom for stability.

DIMENSIONS, ABF-1DB(C): Box only: 9.938" (25.24 cm) high x 4.625" (11.75 cm) wide x 2.5" (6.35 cm) deep. Door: 11" (27.94 cm) high x 6" (15.24 cm) wide x 0.75" (1.9 cm) deep.

DIMENSIONS, ABF-2DB(C): Box only: 9.938" (25.24 cm) high x 9.188" (23.34 cm) wide x 3.75" (9.525 cm) deep. Door: 11" (27.94 cm) high x 10.375" (26.35 cm) wide x 0.75" (1.9 cm) deep.

DIMENSIONS, ABS-4D(C): Box only: 11.97" (30.40 cm) high x 19.87" (50.47cm) wide x 3.50" (8.89 cm) deep. Door: 11.97" (30.40 cm) high x 19.87" (50.47 cm) wide x 1.25" (3.18 cm) deep.

ABS-2D(C): This surface (or semi-flush) mount backbox is used with the ACS annunciators, the SCS series, NCA-2 and the NCA-2 Black.

ADP-4B: The Annunciator Dress Panel-4B (black) provides for the cabinet mounting of one to four modules. The ADP-4B hinge-mounts to the CAB-4 Series cabinet. Modules mount directly to threaded studs on the dress panel.

DP-DISP: (see figure) The Dress Panel-Display allows one to four modules to be mounted in the top row of the CAB-4 Series backbox. Modules mount directly to threaded studs on the DP-DISP.

DP-DISP2: NFS2-640 Dress Panel accommodates up to two annunciator modules (no expanders).

BMP-1: Annunciator Blank Module is a flat black dress plate that covers unused module positions in the annunciator backbox or in the ADP-4B. 8.375" (21.27 cm) high x 4.375" (11.11 cm) wide. Studs for a variety of module mounting options are available.

AKS-1B: The Annunciator Key Switch-1B (black) provides access security for the control switches on the ACM/AEM-24AT. The key switch kit includes a key and hardware for mounting to the ABF-1B(C). Also included is an adhesive-backed annunciator label for use with the key switch/dress plate assembly. NOTE: The AKS-1B can only be employed with the ABS-1TB(C).

Agency Listings and Approvals

The listings and approvals below apply to the ACM/AEM-24AT and the ACM/AEM-48A. In some cases, certain modules or

applications may not be listed by certain approval agencies, or listing may be in process. Consult factory for latest listing status.
UL: S635
ULC: S527-11
FDNY: COA #6212 (NFS2-640), COA #6211 (NFS2-3030)
CSFM: 7120-0028:0156, 7165-0028:0243, 7165-0028:0224
FM approved
50439d1.tif
ABF-4B
DP-DISP Dress Panel with NCA-2 Network Control Annunciator in left two positions, and two ACM-24AT Annunciators at right.
6858disp.wmf

ONYX® and NOTIFIER® are registered trademarks of Honeywell International Inc.
of this document is strictly prohibited.
- This document is not intended to be used for installation purposes.
- We try to keep our product information up-to-date and accurate.
We cannot cover all specific applications or anticipate all requirements.
All specifications are subject to change without notice.
For more information, contact Notifier. Phone: (203) 484-7161, FAX: (203) 484-7118.
Country of Origin: USA

RimelT · Toluca, Estado de México · Comprobante interno NO fiscal · si requieres CFDI 4.0 solicítalo en tu cuenta de cliente. | 09/11/2026 21:51